

Radio-over-IP Gateway

TRBOnet Swift A200

The Swift A200 gateway enables a system owner to connect a remote base radio to TRBOnet Enterprise or Plus without the need to install a computer. Depending on the system design, the gateway can route voice and data from and to one or many connected TRBOnet Servers over IP.





Size: 82 x 35 x 102 mm


Weight: 0.2 kg


ADVANTAGES AND BENEFITS

- You can monitor remote sites from a central location
- LAN connection enables multiple gateways
- The unit doesn't require a sound card
- A200 can work with latency up to 1800ms*
- Smooth analog-to-digital migration

- Can be connected to some analog and digital non-MOTOTRBO base radios
- Enables patching between analog and digital channels
- TRBOnet shows the connection status, temperature and sensor information
- Remote channel change (MOTOTRBO only)

^{*}requires Enterprise/Plus 5.2.5 or newer





FEATURES

- Compatible with MOTOTRBO radios: DM4000 (EMEA), XPR 5000 (NAR), DGM 5000, DGM 8000 (LACR), and XiR M8600i, XiR M8600, XiR M6660 (APAC)*
- Support for voice and data traffic (MOTOTRBO radios)
- Can be connected to certain analog and non-MOTOTRBO digital radios*
- Support for voice traffic (non-MOTOTRBO radios)
- Wired connection to a base radio Support for up to 10 TRBOnet Servers
 - Compact design
 - **OLED** display
 - 7 configurable input/output contacts

SPECIFICATION

GENERAL

Dimensions 82 x 35 x 102 mm

Weight 0.2 kg

Operational temperature -20 °C to 60 °C 85% at +40 °C Relative humidity, max

POWER SUPPLY

12 V DC Power input voltage

7 I/O, micro-USB, USB, LAN, UART, Audio In/Out **INTERFACES** RJ45, Ethernet 10/100Base-T, 10/100 Mbit/s LAN INTERFACE

RADIO CONNECTION INTERFACES

USB (wired), NRF (wireless) MOTOTRBO Audio (wired) + Control (PTT, CSQ) Non-MOTOTRBO









Sales & Support

For Sales & Support please contact your local TRBOnet dealer or visit www.trbonet.com for a complete list of dealers in your region.

EMEA Americas APAC

+44 203 6080598 +61 28 6078325 + 1 872 222 8726



^{*}the radio must be purchased separately